

Pico's New 300 Watts Series XPB

Features:

- Input Over Voltage Protection
- Output Voltage Protection (Latched)
- Over Tem. Shutdown
- Tight Load and Line Regulation
- No External Components Needed
- High Density/High Efficiency
- Remote Shutdown
- Trim Capabilities
- In/Out Synchronization
- Fixed/Frequency Operation

Typical Characteristics:

- Storage Temp.: -55° C to +105° C
- Frequency: 300 Khz (Fixed)
- Baseplate Temp.: +85° C
- Operation Temp.: See Thermal Chart and Application Notes
- Test Condition: +25° C (Room. Temp.)
- Isolation:
Input-Output 2000V DC
Input Baseplate 2000V DC
Output Baseplate 1000V DC

High Power Series XPB 36 - 72V DC

Pico Part Number	Input Voltage Range	Output Voltage DC	Max. Load Current (A)	Max. Output Power (Watts)	Eff. @ Full Load Typical (A)	Input Current Full Load Typical (%)	Output Ripple @ Full Load 1-1MHz BW Mv p-p	Out Volt Tolerance (±%)*	LD Reg 10%-100% Load (±%)*	Line Regulation (±%)*	Price (US \$)
XPB3.3S	36-72	3.3	30.3	100	79	3.86	50	1.0	0.75	0.5	307.16
XPB5S	36-72	5	30	150	81	3.86	50	0.75	0.5	0.5	307.16
XPB5.2S	36-72	5.2	28.8	150	81	3.86	50	0.75	0.5	0.5	307.16
XPB9S	36-72	9	27.8	250	85	6.13	50	0.5	0.5	0.5	307.16
XPB12S	36-72	12	22.9	275	86	6.67	50	0.5	0.5	0.5	307.16
XPB15S	36-72	15	18.3	275	86	6.67	50	0.5	0.5	0.5	307.16
XPB24S	36-72	24	12.5	300	86	7.27	75	0.3	0.3	0.2	307.16
XPB28S	36-72	28	10.7	300	87	7.18	75	0.3	0.3	0.2	307.16



* THESE ARE TYPICAL RESISTANCE VALUES, AS EACH INDIVIDUAL UNIT WILL VARY SLIGHTLY.
USE OF TRIM POT TO DETERMINE RESISTANCE VALUE IS RECOMMENDED.
USE 1/2 WATT MINIMUM POWER RATING RESISTOR.

[GO TO APPLICATION NOTES](#)

Note: If remote sense is not used, + Sense to + Output and - Sense to - Output must be connected for proper operation. Otherwise the unit will be in

shutdown mode.

For immediate engineering assistance or to place an order - **Call Toll Free 800-431-1064**

PICO Electronics, Inc.

143 Sparks Avenue, Pelham, N.Y. 10803

Fax: (914)-738-8225