

## **L-8510**

Submitted by billnbdadmin on Wed, 07/24/2013 - 10:51

### **Product type:**

- [Audio Transformers](#)

### **Price:**

54.840

### **Secondary Impedance Ohms Split Windings SER:**

3600 ct

### **Primary Impedance Ohms:**

3600.000

### **Secondary Impedance Ohms Split Windings PAR:**

900.000

### **Power Watts 1 KHz and higher:**

0.600

### **Power Watts 400 Hz and higher:**

0.400

**Power Watts 300 Hz and higher:**

0.300

**Primary Unbalanced DC Current ma:**

2.500

**Primary DC Resistance Ohms:**

330.000

**Secondary DC Resistance Ohms SER CONN:**

366.000

**Secondary DC Resistance Ohms PAR CONN:**

92.000

**Turns Ratio Prim/Sec SEC SER CONN:**

1:01

**Turns Ratio Prim/Sec SEC PAR CONN:**

2:01

**Product Sub-type:**

- [Thru Hole](#)

## Frequency:

- [1 KHz](#)
- [400 Hz](#)
- [300 Hz](#)

## Series:

- [Series L and P](#)

## Primary Impedance Ohms\_text:

3600 ct

## Frequency Response Range:

- [300 Hz to 75 KHz](#)

## Frequency Response:

3

## Maximum Voltage at 1 KHz (Volt):

46.48

## Maximum Voltage at 400 Hz (Volt):

37.95

## Maximum Voltage at 300 Hz (Volt):

32.86

**Custom Link:**

13249