

## W-26285

Submitted by billnbdadmin on Tue, 07/23/2013 - 10:58

### **Product type:**

- [Audio Transformers](#)

### **Price:**

41.540

### **Secondary Impedance Ohms Split Windings SER:**

500 ct

### **Primary Impedance Ohms:**

1200.000

### **Secondary Impedance Ohms Split Windings PAR:**

125.000

### **Power Watts 1 KHz and higher:**

0.400

### **Power Watts 400 Hz and higher:**

0.075

**Primary Unbalanced DC Current ma:**

2.900

**Primary DC Resistance Ohms:**

120.000

**Secondary DC Resistance Ohms SER CONN:**

60.000

**Secondary DC Resistance Ohms PAR CONN:**

15.000

**Turns Ratio Prim/Sec SEC SER CONN:**

1.55:1

**Turns Ratio Prim/Sec SEC PAR CONN:**

3.1:1

**Product Sub-type:**

- [Thru Hole](#)

**Frequency:**

- [1 KHz](#)
- [400 Hz](#)

## Series:

- [Series W](#)

## Primary Impedance Ohms\_text:

1200 ct

## Frequency Response Range:

- [400 Hz to 100 KHz](#)

## Frequency Response:

3

## Maximum Voltage at 1 KHz (Volt):

21.91

## Maximum Voltage at 400 Hz (Volt):

9.49

## Custom Link:

13247