

## **R-20360**

Submitted by billnbdadmin on Tue, 07/23/2013 - 16:43

### **Product type:**

- [Audio Transformers](#)

### **Price:**

82.130

### **Secondary Impedance Ohms Split Windings SER:**

12.8 ct

### **Primary Impedance Ohms:**

8000.000

### **Secondary Impedance Ohms Split Windings PAR:**

3.200

### **Power Watts 1 KHz and higher:**

1.200

### **Power Watts 300 Hz and higher:**

0.900

**Primary Unbalanced DC Current ma:**

1.100

**Primary DC Resistance Ohms:**

640.000

**Secondary DC Resistance Ohms SER CONN:**

1.220

**Secondary DC Resistance Ohms PAR CONN:**

0.300

**Turns Ratio Prim/Sec SEC SER CONN:**

25:01:00

**Turns Ratio Prim/Sec SEC PAR CONN:**

50:01:00

**Power Watts 75 Hz and higher:**

0.030

**Product Sub-type:**

- [Thru Hole](#)

## Frequency:

- [1 KHz](#)
- [300 Hz](#)
- [75 Hz](#)

## Series:

- [Series R](#)

## Primary Impedance Ohms\_text:

8000 ct

## Frequency Response Range:

- [75 Hz to 30 KHz](#)

## Frequency Response:

3

## Maximum Voltage at 1 KHz (Volt):

97.98

## Maximum Voltage at 300 Hz (Volt):

84.85

## Maximum Voltage at 75 Hz (Volt):

15.49

**Custom Link:**

13251