

R-20380

Submitted by billnbdadmin on Tue, 07/23/2013 - 16:43

Product type:

- [Audio Transformers](#)

Price:

82.130

Secondary Impedance Ohms Split Windings SER:

12.8 ct

Primary Impedance Ohms:

10000.000

Secondary Impedance Ohms Split Windings PAR:

3.200

Power Watts 1 KHz and higher:

1.000

Power Watts 300 Hz and higher:

0.900

Primary Unbalanced DC Current ma:

1.000

Primary DC Resistance Ohms:

800.000

Secondary DC Resistance Ohms SER CONN:

1.220

Secondary DC Resistance Ohms PAR CONN:

0.300

Turns Ratio Prim/Sec SEC SER CONN:

28:01:00

Turns Ratio Prim/Sec SEC PAR CONN:

56:01:00

Power Watts 75 Hz and higher:

0.030

Product Sub-type:

- [Thru Hole](#)

Frequency:

- [1 KHz](#)
- [300 Hz](#)
- [75 Hz](#)

Series:

- [Series R](#)

Primary Impedance Ohms_text:

10,000 ct

Frequency Response Range:

- [75 Hz to 30 KHz](#)

Frequency Response:

3

Maximum Voltage at 1 KHz (Volt):

100.00

Maximum Voltage at 300 Hz (Volt):

94.87

Maximum Voltage at 75 Hz (Volt):

17.32

Custom Link:

13251