

## **R-20385**

Submitted by billnbdadmin on Tue, 07/23/2013 - 16:43

### **Product type:**

- [Audio Transformers](#)

### **Price:**

82.130

### **Secondary Impedance Ohms Split Windings SER:**

16 ct

### **Primary Impedance Ohms:**

10000.000

### **Secondary Impedance Ohms Split Windings PAR:**

4.000

### **Power Watts 1 KHz and higher:**

1.000

### **Power Watts 300 Hz and higher:**

0.900

**Primary Unbalanced DC Current ma:**

1.000

**Primary DC Resistance Ohms:**

800.000

**Secondary DC Resistance Ohms SER CONN:**

1.520

**Secondary DC Resistance Ohms PAR CONN:**

0.380

**Turns Ratio Prim/Sec SEC SER CONN:**

25:01:00

**Turns Ratio Prim/Sec SEC PAR CONN:**

50:01:00

**Power Watts 75 Hz and higher:**

0.030

**Product Sub-type:**

- [Thru Hole](#)

## Frequency:

- [1 KHz](#)
- [300 Hz](#)
- [75 Hz](#)

## Series:

- [Series R](#)

## Primary Impedance Ohms\_text:

10,000 ct

## Frequency Response Range:

- [75 Hz to 30 KHz](#)

## Frequency Response:

3

## Maximum Voltage at 1 KHz (Volt):

100.00

## Maximum Voltage at 300 Hz (Volt):

94.87

## Maximum Voltage at 75 Hz (Volt):

17.32

**Custom Link:**

13251