

R-20480

Submitted by billnbdadmin on Tue, 07/23/2013 - 16:43

Product type:

- [Audio Transformers](#)

Price:

87.570

Secondary Impedance Ohms Split Windings SER:

500 ct

Primary Impedance Ohms:

20000.000

Secondary Impedance Ohms Split Windings PAR:

125.000

Power Watts 1 KHz and higher:

0.500

Power Watts 300 Hz and higher:

0.500

Primary Unbalanced DC Current ma:

0.700

Primary DC Resistance Ohms:

1600.000

Secondary DC Resistance Ohms SER CONN:

47.500

Secondary DC Resistance Ohms PAR CONN:

11.880

Turns Ratio Prim/Sec SEC SER CONN:

6.32:1

Turns Ratio Prim/Sec SEC PAR CONN:

12.65:1

Power Watts 75 Hz and higher:

0.030

Product Sub-type:

- [Thru Hole](#)

Frequency:

- [1 KHz](#)
- [300 Hz](#)
- [75 Hz](#)

Series:

- [Series R](#)

Primary Impedance Ohms_text:

20,000 ct

Frequency Response Range:

- [75 Hz to 30 KHz](#)

Frequency Response:

3

Maximum Voltage at 1 KHz (Volt):

100.00

Maximum Voltage at 300 Hz (Volt):

100.00

Maximum Voltage at 75 Hz (Volt):

24.49

Custom Link:

13251