

# 71045

Submitted by billnbdadmin on Fri, 07/19/2013 - 10:33

## **Product type:**

- [Audio Transformers](#)

## **Price:**

46.230

## **Secondary Impedance Ohms Split Windings SER:**

100 ct

## **Primary Impedance Ohms:**

100.000

## **Secondary Impedance Ohms Split Windings PAR:**

25.000

## **Power Watts 1 KHz and higher:**

0.400

## **Power Watts 400 Hz and higher:**

0.075

**Primary Unbalanced DC Current ma:**

10.000

**Primary DC Resistance Ohms:**

10.000

**Secondary DC Resistance Ohms SER CONN:**

12.000

**Secondary DC Resistance Ohms PAR CONN:**

3.000

**Turns Ratio Prim/Sec SEC SER CONN:**

1:01

**Turns Ratio Prim/Sec SEC PAR CONN:**

2:01

**Product Sub-type:**

- [Surface Mount Gull Lead Square](#)

**Terminals:**

- [Surface Mount](#)

## Frequency:

- [1 KHz](#)
- [400 Hz](#)

## Series:

- [Series 71000 and 81000](#)

## Primary Impedance Ohms\_text:

100 ct

## Frequency Response Range:

- [400 Hz to 100 KHz](#)

## Frequency Response:

3

## Maximum Voltage at 1 KHz (Volt):

6.32

## Maximum Voltage at 400 Hz (Volt):

2.74

## Custom Link:

13353