# 71595

Submitted by billnbdadmin on Fri, 07/19/2013 - 10:33

## Product type:

- Audio Transformers

## Price:

63.220

## Secondary Impedance Ohms Split Windings SER:

1200 ct

## Primary Impedance Ohms:

30000.000

## Secondary Impedance Ohms Split Windings PAR:

300.000

## Power Watts 1 KHz and higher:

0.083

## Power Watts 400 Hz and higher:

0.075

## Primary Unbalanced DC Current ma:

0.580

## Primary DC Resistance Ohms:

3000.000

## Secondary DC Resistance Ohms SER CONN:

144.000

## Secondary DC Resistance Ohms PAR CONN:

36.000

## Turns Ratio Prim/Sec SEC SER CONN:

5:01

## Turns Ratio Prim/Sec SEC PAR CONN:

10:01

## Product Sub-type:

- Surface Mount Gull Lead Square

## Terminals:

- Surface Mount

## Frequency:

- 1 KHz
- 400 Hz

## Series:

- Series 71000 and 81000

## Primary Impedance Ohms_text:

30,000 ct

## Frequency Response Range:

- 400 Hz to 100 KHz

## Frequency Response:

3

## Maximum Voltage at 1 KHz (Volt):

49.90

## Maximum Voltage at 400 Hz (Volt):

47.43

## Custom Link:

13353