

81200

Submitted by billnbdadmin on Fri, 07/19/2013 - 10:33

Product type:

- [Audio Transformers](#)

Price:

48.440

Secondary Impedance Ohms Split Windings SER:

30 ct

Primary Impedance Ohms:

600.000

Secondary Impedance Ohms Split Windings PAR:

7.500

Power Watts 1 KHz and higher:

0.400

Power Watts 400 Hz and higher:

0.075

Primary Unbalanced DC Current ma:

4.100

Primary DC Resistance Ohms:

60.000

Secondary DC Resistance Ohms SER CONN:

3.600

Secondary DC Resistance Ohms PAR CONN:

0.900

Turns Ratio Prim/Sec SEC SER CONN:

4.47:1

Turns Ratio Prim/Sec SEC PAR CONN:

8.94:1

Product Sub-type:

- [Surface Mount "J" Lead](#)

Terminals:

- [Surface Mount "J" Lead](#)

Frequency:

- [1 KHz](#)
- [400 Hz](#)

Series:

- [Series 71000 and 81000](#)

Primary Impedance Ohms_text:

600 ct

Frequency Response Range:

- [400 Hz to 100 KHz](#)

Frequency Response:

3

Maximum Voltage at 1 KHz (Volt):

15.49

Maximum Voltage at 400 Hz (Volt):

6.71

Power Watts 400 Hz and higher Tag:

- [0.075](#)

Power Watts 1 KHz and higher Tag:

- [0.400](#)

Custom Link:

13353