

**80085**

Submitted by billnbdadmin on Mon, 07/22/2013 - 17:15

**Product type:**

- [Audio Transformers](#)

**Price:**

71.370

**Secondary Impedance Ohms Split Windings SER:**

600 ct

**Primary Impedance Ohms:**

150.000

**Secondary Impedance Ohms Split Windings PAR:**

150.000

**Power Watts 1 KHz and higher:**

0.125

**Power Watts 400 Hz and higher:**

0.020

**Primary Unbalanced DC Current ma:**

3.000

**Primary DC Resistance Ohms:**

15.000

**Secondary DC Resistance Ohms SER CONN:**

72.000

**Secondary DC Resistance Ohms PAR CONN:**

18.000

**Turns Ratio Prim/Sec SEC SER CONN:**

1:02

**Turns Ratio Prim/Sec SEC PAR CONN:**

1:01

**Product Sub-type:**

- [Surface Mount "J" Lead](#)

**Terminals:**

- [Surface Mount "J" Lead](#)

## Frequency:

- [1 KHz](#)
- [400 Hz](#)

## Series:

- [Series 70000 and 80000](#)

## Primary Impedance Ohms\_text:

150 ct

## Frequency Response Range:

- [400 Hz to 250 KHz](#)

## Frequency Response:

3

## Maximum Voltage at 1 KHz (Volt):

4.33

## Maximum Voltage at 400 Hz (Volt):

1.73

## Power Watts 400 Hz and higher Tag:

- [0.020](#)

## **Power Watts 1 KHz and higher Tag:**

- [0.125](#)

## **Custom Link:**

13352