

80155

Submitted by billnbdadmin on Mon, 07/22/2013 - 17:15

Product type:

- [Audio Transformers](#)

Price:

76.520

Secondary Impedance Ohms Split Windings SER:

4000 ct

Primary Impedance Ohms:

400.000

Secondary Impedance Ohms Split Windings PAR:

1000.000

Power Watts 1 KHz and higher:

0.125

Power Watts 400 Hz and higher:

0.020

Primary Unbalanced DC Current ma:

1.800

Primary DC Resistance Ohms:

49.000

Secondary DC Resistance Ohms SER CONN:

476.000

Secondary DC Resistance Ohms PAR CONN:

119.000

Turns Ratio Prim/Sec SEC SER CONN:

01:03.2

Turns Ratio Prim/Sec SEC PAR CONN:

01:01.6

Product Sub-type:

- [Surface Mount "J" Lead](#)

Terminals:

- [Surface Mount "J" Lead](#)

Frequency:

- [1 KHz](#)
- [400 Hz](#)

Series:

- [Series 70000 and 80000](#)

Primary Impedance Ohms_text:

400 ct

Frequency Response Range:

- [400 Hz to 250 KHz](#)

Frequency Response:

3

Maximum Voltage at 1 KHz (Volt):

7.07

Maximum Voltage at 400 Hz (Volt):

2.83

Power Watts 400 Hz and higher Tag:

- [0.020](#)

Power Watts 1 KHz and higher Tag:

- [0.125](#)

Custom Link:

13352