

## **RPS-76350**

Submitted by billnbdadmin on Tue, 05/10/2016 - 23:12

### **Product type:**

- [Audio Transformers](#)

### **Price:**

50.320

### **Secondary Impedance Ohms Split Windings SER:**

500 ct

### **Primary Impedance Ohms:**

500.000

### **Secondary Impedance Ohms Split Windings PAR:**

125.000

### **Power Watts 1 KHz and higher:**

0.600

### **Primary Unbalanced DC Current ma:**

6.000

**Primary DC Resistance Ohms:**

48.000

**Secondary DC Resistance Ohms SER CONN:**

54.000

**Secondary DC Resistance Ohms PAR CONN:**

13.500

**Turns Ratio Prim/Sec SEC SER CONN:**

1:01

**Turns Ratio Prim/Sec SEC PAR CONN:**

2:01

**Product Sub-type:**

- [Surface Mount Gull Lead Round](#)

**Primary Impedance Ohms\_text:**

500 ct

**Frequency Response Range:**

- [300 Hz to 75 KHz](#)

## **Frequency Response:**

3

**Maximum Voltage at 1 KHz (Volt):**

17.32

**Maximum Voltage at 400 Hz (Volt):**

14.14

**Maximum Voltage at 300 Hz (Volt):**

12.25