

## **RPS-82030**

Submitted by billnbdadmin on Tue, 05/10/2016 - 23:12

### **Product type:**

- [Audio Transformers](#)

### **Price:**

61.540

### **Secondary Impedance Ohms Split Windings SER:**

100 ct

### **Primary Impedance Ohms:**

100.000

### **Secondary Impedance Ohms Split Windings PAR:**

25.000

### **Power Watts 1 KHz and higher:**

1.500

### **Primary Unbalanced DC Current ma:**

10.000

**Primary DC Resistance Ohms:**

8.000

**Secondary DC Resistance Ohms SER CONN:**

9.500

**Secondary DC Resistance Ohms PAR CONN:**

2.380

**Turns Ratio Prim/Sec SEC SER CONN:**

1:01

**Turns Ratio Prim/Sec SEC PAR CONN:**

2:01

**Power Watts 75 Hz and higher:**

0.030

**Product Sub-type:**

- [Surface Mount Gull Lead Round](#)

**Primary Impedance Ohms\_text:**

100 ct

## **Frequency Response Range:**

- [75 Hz to 30 KHz](#)

## **Frequency Response:**

3

## **Maximum Voltage at 1 KHz (Volt):**

12.25

## **Maximum Voltage at 300 Hz (Volt):**

9.49

## **Maximum Voltage at 75 Hz (Volt):**

1.73