

## **RPS-83003**

Submitted by billnbdadmin on Tue, 05/10/2016 - 23:12

### **Product type:**

- [Audio Transformers](#)

### **Price:**

50.190

### **Secondary Impedance Ohms Split Windings SER:**

8 ct

### **Primary Impedance Ohms:**

20.000

### **Secondary Impedance Ohms Split Windings PAR:**

2.000

### **Power Watts 1 KHz and higher:**

2.000

### **Primary Unbalanced DC Current ma:**

22.000

**Primary DC Resistance Ohms:**

1.600

**Secondary DC Resistance Ohms SER CONN:**

0.880

**Secondary DC Resistance Ohms PAR CONN:**

0.220

**Turns Ratio Prim/Sec SEC SER CONN:**

1.58:1

**Turns Ratio Prim/Sec SEC PAR CONN:**

3.16:1

**Power Watts 50 Hz and higher:**

0.030

**Product Sub-type:**

- [Surface Mount Gull Lead Round](#)

**Primary Impedance Ohms\_text:**

20 ct

## **Frequency Response Range:**

- [50 Hz to 30 KHz](#)

## **Frequency Response:**

3

## **Maximum Voltage at 1 KHz (Volt):**

6.32

## **Maximum Voltage at 300 Hz (Volt):**

5.48

## **Maximum Voltage at 50 Hz (Volt):**

0.77