

RPS-83028

Submitted by billnbdadmin on Tue, 05/10/2016 - 23:12

Product type:

- [Audio Transformers](#)

Price:

50.190

Secondary Impedance Ohms Split Windings SER:

40 ct

Primary Impedance Ohms:

100.000

Secondary Impedance Ohms Split Windings PAR:

10.000

Power Watts 1 KHz and higher:

2.000

Primary Unbalanced DC Current ma:

10.000

Primary DC Resistance Ohms:

8.000

Secondary DC Resistance Ohms SER CONN:

4.400

Secondary DC Resistance Ohms PAR CONN:

1.100

Turns Ratio Prim/Sec SEC SER CONN:

1.58:1

Turns Ratio Prim/Sec SEC PAR CONN:

3.16:1

Power Watts 50 Hz and higher:

0.030

Product Sub-type:

- [Surface Mount Gull Lead Round](#)

Primary Impedance Ohms_text:

100 ct

Frequency Response Range:

- [50 Hz to 30 KHz](#)

Frequency Response:

3

Maximum Voltage at 1 KHz (Volt):

14.14

Maximum Voltage at 300 Hz (Volt):

12.25

Maximum Voltage at 50 Hz (Volt):

1.73