

RPS-83160

Submitted by billnbdadmin on Tue, 05/10/2016 - 23:12

Product type:

- [Audio Transformers](#)

Price:

50.190

Secondary Impedance Ohms Split Windings SER:

600 ct

Primary Impedance Ohms:

500.000

Secondary Impedance Ohms Split Windings PAR:

150.000

Power Watts 1 KHz and higher:

2.000

Primary Unbalanced DC Current ma:

4.500

Primary DC Resistance Ohms:

40.000

Secondary DC Resistance Ohms SER CONN:

66.000

Secondary DC Resistance Ohms PAR CONN:

16.500

Turns Ratio Prim/Sec SEC SER CONN:

01:01.1

Turns Ratio Prim/Sec SEC PAR CONN:

1.83:1

Power Watts 50 Hz and higher:

0.030

Product Sub-type:

- [Surface Mount Gull Lead Round](#)

Primary Impedance Ohms_text:

500 ct

Frequency Response Range:

- [50 Hz to 30 KHz](#)

Frequency Response:

3

Maximum Voltage at 1 KHz (Volt):

31.62

Maximum Voltage at 300 Hz (Volt):

27.39

Maximum Voltage at 50 Hz (Volt):

3.87