

RPS-83300

Submitted by billnbdadmin on Tue, 05/10/2016 - 23:12

Product type:

- [Audio Transformers](#)

Price:

52.380

Secondary Impedance Ohms Split Windings SER:

3000 ct

Primary Impedance Ohms:

3000.000

Secondary Impedance Ohms Split Windings PAR:

750.000

Power Watts 1 KHz and higher:

2.000

Primary Unbalanced DC Current ma:

1.800

Primary DC Resistance Ohms:

240.000

Secondary DC Resistance Ohms SER CONN:

330.000

Secondary DC Resistance Ohms PAR CONN:

83.000

Turns Ratio Prim/Sec SEC SER CONN:

1:01

Turns Ratio Prim/Sec SEC PAR CONN:

2:01

Power Watts 50 Hz and higher:

0.030

Product Sub-type:

- [Surface Mount Gull Lead Round](#)

Primary Impedance Ohms_text:

3000 ct

Frequency Response Range:

- [50 Hz to 30 KHz](#)

Frequency Response:

3

Maximum Voltage at 1 KHz (Volt):

77.46

Maximum Voltage at 300 Hz (Volt):

67.08

Maximum Voltage at 50 Hz (Volt):

9.49