

RPS-83405

Submitted by billnbdadmin on Tue, 05/10/2016 - 23:12

Product type:

- [Audio Transformers](#)

Price:

55.590

Secondary Impedance Ohms Split Windings SER:

600 ct

Primary Impedance Ohms:

10.000

Secondary Impedance Ohms Split Windings PAR:

150.000

Power Watts 1 KHz and higher:

1.000

Primary Unbalanced DC Current ma:

1.000

Primary DC Resistance Ohms:

800.000

Secondary DC Resistance Ohms SER CONN:

66.000

Secondary DC Resistance Ohms PAR CONN:

16.500

Turns Ratio Prim/Sec SEC SER CONN:

4.08:1

Turns Ratio Prim/Sec SEC PAR CONN:

8.16:1

Power Watts 50 Hz and higher:

0.030

Product Sub-type:

- [Surface Mount Gull Lead Round](#)

Primary Impedance Ohms_text:

10,000 ct

Frequency Response Range:

- [50 Hz to 30 KHz](#)

Frequency Response:

3

Maximum Voltage at 1 KHz (Volt):

100.00

Maximum Voltage at 300 Hz (Volt):

100.00

Maximum Voltage at 50 Hz (Volt):

17.32