

Y-27040

Submitted by billnbdadmin on Tue, 07/23/2013 - 08:59

Product type:

- [Audio Transformers](#)

Price:

60.700

Secondary Impedance Ohms Split Windings SER:

40 ct

Primary Impedance Ohms:

100.000

Secondary Impedance Ohms Split Windings PAR:

10.000

Power Watts 1 KHz and higher:

0.600

Power Watts 400 Hz and higher:

0.200

Power Watts 300 Hz and higher:

0.200

Primary Unbalanced DC Current ma:

10.000

Primary DC Resistance Ohms:

10.000

Secondary DC Resistance Ohms SER CONN:

4.500

Secondary DC Resistance Ohms PAR CONN:

1.130

Turns Ratio Prim/Sec SEC SER CONN:

1.58:1

Turns Ratio Prim/Sec SEC PAR CONN:

3.16:1

Product Sub-type:

- [Thru Hole](#)

Frequency:

- [1 KHz](#)
- [400 Hz](#)
- [300 Hz](#)

Series:

- [Series Y](#)

Primary Impedance Ohms_text:

100 ct

Frequency Response Range:

- [300 Hz to 100 KHz](#)

Frequency Response:

3

Maximum Voltage at 1 KHz (Volt):

7.75

Maximum Voltage at 400 Hz (Volt):

4.47

Maximum Voltage at 300 Hz (Volt):

3.16

Custom Link:

13248