

## Y-27345

Submitted by billnbdadmin on Tue, 07/23/2013 - 08:59

### **Product type:**

- [Audio Transformers](#)

### **Price:**

60.190

### **Secondary Impedance Ohms Split Windings SER:**

2500 ct

### **Primary Impedance Ohms:**

2500.000

### **Secondary Impedance Ohms Split Windings PAR:**

625.000

### **Power Watts 1 KHz and higher:**

0.600

### **Power Watts 400 Hz and higher:**

0.200

**Power Watts 300 Hz and higher:**

0.200

**Primary Unbalanced DC Current ma:**

2.000

**Primary DC Resistance Ohms:**

250.000

**Secondary DC Resistance Ohms SER CONN:**

300.000

**Secondary DC Resistance Ohms PAR CONN:**

75.000

**Turns Ratio Prim/Sec SEC SER CONN:**

1:01

**Turns Ratio Prim/Sec SEC PAR CONN:**

2:01

**Product Sub-type:**

- [Thru Hole](#)

## Frequency:

- [1 KHz](#)
- [400 Hz](#)
- [300 Hz](#)

## Series:

- [Series Y](#)

## Primary Impedance Ohms\_text:

2500 ct

## Frequency Response Range:

- [300 Hz to 100 KHz](#)

## Frequency Response:

3

## Maximum Voltage at 1 KHz (Volt):

38.73

## Maximum Voltage at 400 Hz (Volt):

22.36

## Maximum Voltage at 300 Hz (Volt):

15.81

**Custom Link:**

13248