

Y-27365

Submitted by billnbdadmin on Tue, 07/23/2013 - 08:59

Product type:

- [Audio Transformers](#)

Price:

60.190

Secondary Impedance Ohms Split Windings SER:

16 ct

Primary Impedance Ohms:

4000.000

Secondary Impedance Ohms Split Windings PAR:

4.000

Power Watts 1 KHz and higher:

0.600

Power Watts 400 Hz and higher:

0.200

Power Watts 300 Hz and higher:

0.200

Primary Unbalanced DC Current ma:

1.600

Primary DC Resistance Ohms:

400.000

Secondary DC Resistance Ohms SER CONN:

1.920

Secondary DC Resistance Ohms PAR CONN:

0.480

Turns Ratio Prim/Sec SEC SER CONN:

15.8:1

Turns Ratio Prim/Sec SEC PAR CONN:

31.6:1

Product Sub-type:

- [Thru Hole](#)

Frequency:

- [1 KHz](#)
- [400 Hz](#)
- [300 Hz](#)

Series:

- [Series Y](#)

Primary Impedance Ohms_text:

4000 ct

Frequency Response Range:

- [300 Hz to 100 KHz](#)

Frequency Response:

3

Maximum Voltage at 1 KHz (Volt):

48.99

Maximum Voltage at 400 Hz (Volt):

28.28

Maximum Voltage at 300 Hz (Volt):

20.00

Custom Link:

13248