

## Y-27495

Submitted by billnbdadmin on Tue, 07/23/2013 - 08:59

### **Product type:**

- [Audio Transformers](#)

### **Price:**

59.500

### **Secondary Impedance Ohms Split Windings SER:**

7500 ct

### **Primary Impedance Ohms:**

10000.000

### **Secondary Impedance Ohms Split Windings PAR:**

1875.000

### **Power Watts 1 KHz and higher:**

0.250

### **Power Watts 400 Hz and higher:**

0.200

**Power Watts 300 Hz and higher:**

0.200

**Primary Unbalanced DC Current ma:**

1.000

**Primary DC Resistance Ohms:**

1000.000

**Secondary DC Resistance Ohms SER CONN:**

900.000

**Secondary DC Resistance Ohms PAR CONN:**

225.000

**Turns Ratio Prim/Sec SEC SER CONN:**

1.15:1

**Turns Ratio Prim/Sec SEC PAR CONN:**

2.3:1

**Product Sub-type:**

- [Thru Hole](#)

## Frequency:

- [1 KHz](#)
- [400 Hz](#)
- [300 Hz](#)

## Series:

- [Series Y](#)

## Primary Impedance Ohms\_text:

10,000 ct

## Frequency Response Range:

- [300 Hz to 100 KHz](#)

## Frequency Response:

3

## Maximum Voltage at 1 KHz (Volt):

50.00

## Maximum Voltage at 400 Hz (Volt):

44.72

## Maximum Voltage at 300 Hz (Volt):

31.62

**Custom Link:**

13248