

## Y-27600

Submitted by billnbdadmin on Tue, 07/23/2013 - 08:59

### **Product type:**

- [Audio Transformers](#)

### **Price:**

58.100

### **Secondary Impedance Ohms Split Windings SER:**

500 ct

### **Primary Impedance Ohms:**

30000.000

### **Secondary Impedance Ohms Split Windings PAR:**

125.000

### **Power Watts 1 KHz and higher:**

0.080

### **Power Watts 400 Hz and higher:**

0.080

**Power Watts 300 Hz and higher:**

0.080

**Primary Unbalanced DC Current ma:**

0.580

**Primary DC Resistance Ohms:**

3000.000

**Secondary DC Resistance Ohms SER CONN:**

60.000

**Secondary DC Resistance Ohms PAR CONN:**

15.000

**Turns Ratio Prim/Sec SEC SER CONN:**

7.75:1

**Turns Ratio Prim/Sec SEC PAR CONN:**

15.5:1

**Product Sub-type:**

- [Thru Hole](#)

## Frequency:

- [1 KHz](#)
- [400 Hz](#)
- [300 Hz](#)

## Series:

- [Series Y](#)

## Primary Impedance Ohms\_text:

30,000 ct

## Frequency Response Range:

- [300 Hz to 100 KHz](#)

## Frequency Response:

3

## Maximum Voltage at 1 KHz (Volt):

48.99

## Maximum Voltage at 400 Hz (Volt):

48.99

## Maximum Voltage at 300 Hz (Volt):

48.99

**Custom Link:**

13248