

Y-27650

Submitted by billnbdadmin on Tue, 07/23/2013 - 08:59

Product type:

- [Audio Transformers](#)

Price:

67.160

Secondary Impedance Ohms Split Windings SER:

200 ct

Primary Impedance Ohms:

50000.000

Secondary Impedance Ohms Split Windings PAR:

50.000

Power Watts 1 KHz and higher:

0.050

Power Watts 400 Hz and higher:

0.050

Power Watts 300 Hz and higher:

0.050

Primary Unbalanced DC Current ma:

0.450

Primary DC Resistance Ohms:

5000.000

Secondary DC Resistance Ohms SER CONN:

24.000

Secondary DC Resistance Ohms PAR CONN:

6.000

Turns Ratio Prim/Sec SEC SER CONN:

15.8:1

Turns Ratio Prim/Sec SEC PAR CONN:

31.6:1

Product Sub-type:

- [Thru Hole](#)

Frequency:

- [1 KHz](#)
- [400 Hz](#)
- [300 Hz](#)

Series:

- [Series Y](#)

Primary Impedance Ohms_text:

50,000 ct

Frequency Response Range:

- [300 Hz to 100 KHz](#)

Frequency Response:

3

Maximum Voltage at 1 KHz (Volt):

50.00

Maximum Voltage at 400 Hz (Volt):

50.00

Maximum Voltage at 300 Hz (Volt):

50.00

Custom Link:

13248