Y-27665

Submitted by billnbdadmin on Tue, 07/23/2013 - 08:59

Product type:

- Audio Transformers

Price:

67.160

Secondary Impedance Ohms Split Windings SER:

15,000 ct

Primary Impedance Ohms:

60000.000

Secondary Impedance Ohms Split Windings PAR:

3750.000

Power Watts 1 KHz and higher:

0.040

Power Watts 400 Hz and higher:

0.040

Power Watts 300 Hz and higher:

0.040

Primary Unbalanced DC Current ma:

0.410

Primary DC Resistance Ohms:

6000.000

Secondary DC Resistance Ohms SER CONN:

1800.000

Secondary DC Resistance Ohms PAR CONN:

450.000

Turns Ratio Prim/Sec SEC SER CONN:

2:01

Turns Ratio Prim/Sec SEC PAR CONN:

4:01

Product Sub-type:

- Thru Hole

Frequency:

- 1 KHz
- 400 Hz
- 300 Hz

Series:

- Series Y

Primary Impedance Ohms_text:

60,000 ct

Frequency Response Range:

- 300 Hz to 100 KHz

Frequency Response:

3

Maximum Voltage at 1 KHz (Volt):

48.99

Maximum Voltage at 400 Hz (Volt):

48.99

Maximum Voltage at 300 Hz (Volt):

48.99

Custom Link:

13248