Y-27670

Submitted by billnbdadmin on Tue, 07/23/2013 - 08:59

Product type:

- Audio Transformers

Price:

67.160

Secondary Impedance Ohms Split Windings SER:

50 ct

Primary Impedance Ohms:

62500.000

Secondary Impedance Ohms Split Windings PAR:

12.500

Power Watts 1 KHz and higher:

0.040

Power Watts 400 Hz and higher:

0.040

Power Watts 300 Hz and higher:

0.040

Primary Unbalanced DC Current ma:

0.400

Primary DC Resistance Ohms:

6250.000

Secondary DC Resistance Ohms SER CONN:

6.000

Secondary DC Resistance Ohms PAR CONN:

1.500

Turns Ratio Prim/Sec SEC SER CONN:

35.4:1

Turns Ratio Prim/Sec SEC PAR CONN:

70.7:1

Product Sub-type:

- Thru Hole

Frequency:

- 1 KHz
- 400 Hz
- 300 Hz

Series:

- Series Y

Primary Impedance Ohms_text:

62,500 ct

Frequency Response Range:

- 300 Hz to 100 KHz

Frequency Response:

3

Maximum Voltage at 1 KHz (Volt):

50.00

Maximum Voltage at 400 Hz (Volt):

50.00

Maximum Voltage at 300 Hz (Volt):

50.00

Custom Link:

13248