

W-26040

Submitted by billnbdadmin on Tue, 07/23/2013 - 10:58

Product type:

- [Audio Transformers](#)

Price:

48.890

Secondary Impedance Ohms Split Windings SER:

40 ct

Primary Impedance Ohms:

100.000

Secondary Impedance Ohms Split Windings PAR:

10.000

Power Watts 1 KHz and higher:

0.400

Power Watts 400 Hz and higher:

0.075

Primary Unbalanced DC Current ma:

10.000

Primary DC Resistance Ohms:

10.000

Secondary DC Resistance Ohms SER CONN:

4.500

Secondary DC Resistance Ohms PAR CONN:

1.200

Turns Ratio Prim/Sec SEC SER CONN:

1.58:1

Turns Ratio Prim/Sec SEC PAR CONN:

3.16:1

Product Sub-type:

- [Thru Hole](#)

Frequency:

- [1 KHz](#)
- [400 Hz](#)

Series:

- [Series W](#)

Primary Impedance Ohms_text:

100 ct

Frequency Response Range:

- [400 Hz to 100 KHz](#)

Frequency Response:

3

Maximum Voltage at 1 KHz (Volt):

6.32

Maximum Voltage at 400 Hz (Volt):

2.74

Custom Link:

13247