

W-26545

Submitted by billnbdadmin on Tue, 07/23/2013 - 10:58

Product type:

- [Audio Transformers](#)

Price:

58.120

Secondary Impedance Ohms Split Windings SER:

500 ct

Primary Impedance Ohms:

20000.000

Secondary Impedance Ohms Split Windings PAR:

125.000

Power Watts 1 KHz and higher:

0.125

Power Watts 400 Hz and higher:

0.075

Primary Unbalanced DC Current ma:

0.700

Primary DC Resistance Ohms:

2000.000

Secondary DC Resistance Ohms SER CONN:

60.000

Secondary DC Resistance Ohms PAR CONN:

15.000

Turns Ratio Prim/Sec SEC SER CONN:

6.33:1

Turns Ratio Prim/Sec SEC PAR CONN:

12.65:1

Product Sub-type:

- [Thru Hole](#)

Frequency:

- [1 KHz](#)
- [400 Hz](#)

Series:

- [Series W](#)

Primary Impedance Ohms_text:

20,000 ct

Frequency Response Range:

- [400 Hz to 100 KHz](#)

Frequency Response:

3

Maximum Voltage at 1 KHz (Volt):

50.00

Maximum Voltage at 400 Hz (Volt):

38.73

Custom Link:

13247