

## **S-21345**

Submitted by billnbdadmin on Tue, 07/23/2013 - 14:35

### **Product type:**

- [Audio Transformers](#)

### **Price:**

61.570

### **Secondary Impedance Ohms Split Windings SER:**

600 ct

### **Primary Impedance Ohms:**

7500.000

### **Secondary Impedance Ohms Split Windings PAR:**

150.000

### **Power Watts 1 KHz and higher:**

1.300

### **Power Watts 300 Hz and higher:**

1.300

**Primary Unbalanced DC Current ma:**

1.200

**Primary DC Resistance Ohms:**

600.000

**Secondary DC Resistance Ohms SER CONN:**

66.000

**Secondary DC Resistance Ohms PAR CONN:**

16.500

**Turns Ratio Prim/Sec SEC SER CONN:**

3.54:1

**Turns Ratio Prim/Sec SEC PAR CONN:**

7.07:1

**Power Watts 50 Hz and higher:**

0.030

**Product Sub-type:**

- [Thru Hole](#)

## Frequency:

- [1 KHz](#)
- [300 Hz](#)
- [50 Hz](#)

## Series:

- [Series S](#)

## Primary Impedance Ohms\_text:

7500 ct

## Frequency Response Range:

- [75 Hz to 30 KHz](#)

## Frequency Response:

3

## Maximum Voltage at 1 KHz (Volt):

98.74

## Maximum Voltage at 300 Hz (Volt):

98.74

## Maximum Voltage at 50 Hz (Volt):

15.00

## Custom Link:

13252