

## **K-7625**

Submitted by billnbdadmin on Wed, 07/24/2013 - 09:44

### **Product type:**

- [Audio Transformers](#)

### **Price:**

59.080

### **Secondary Impedance Ohms Split Windings SER:**

2000 ct

### **Primary Impedance Ohms:**

10000.000

### **Secondary Impedance Ohms Split Windings PAR:**

500.000

### **Power Watts 1 KHz and higher:**

1.000

### **Power Watts 400 Hz and higher:**

0.750

**Primary Unbalanced DC Current ma:**

1.000

**Primary DC Resistance Ohms:**

780.000

**Secondary DC Resistance Ohms SER CONN:**

300.000

**Secondary DC Resistance Ohms PAR CONN:**

75.000

**Turns Ratio Prim/Sec SEC SER CONN:**

2.24:1

**Turns Ratio Prim/Sec SEC PAR CONN:**

4.47:1

**Power Watts 150 Hz and higher:**

0.110

**Product Sub-type:**

- [Insulated Leads](#)

## Frequency:

- [1 KHz](#)
- [400 Hz](#)
- [150 Hz](#)

## Series:

- [Series N and K](#)

## Primary Impedance Ohms\_text:

10,000 ct

## Frequency Response Range:

- [150 Hz to 75 KHz](#)

## Frequency Response:

3

## Maximum Voltage at 1 KHz (Volt):

100.00

## Maximum Voltage at 400 Hz (Volt):

86.60

## Maximum Voltage at 150 Hz (Volt):

33.17

## **Power Watts 150 Hz and higher Tag:**

- [0.110](#)

## **Custom Link:**

13250