

L-8355

Submitted by billnbdadmin on Wed, 07/24/2013 - 10:51

Product type:

- [Audio Transformers](#)

Price:

54.840

Secondary Impedance Ohms Split Windings SER:

500 ct

Primary Impedance Ohms:

500.000

Secondary Impedance Ohms Split Windings PAR:

0.000

Power Watts 1 KHz and higher:

0.600

Power Watts 400 Hz and higher:

0.400

Power Watts 300 Hz and higher:

0.300

Primary Unbalanced DC Current ma:

6.000

Primary DC Resistance Ohms:

48.000

Secondary DC Resistance Ohms SER CONN:

68.000

Secondary DC Resistance Ohms PAR CONN:

0.000

Turns Ratio Prim/Sec SEC SER CONN:

1:01

Turns Ratio Prim/Sec SEC PAR CONN:

-

Product Sub-type:

- [Thru Hole](#)

Frequency:

- [1 KHz](#)
- [400 Hz](#)
- [300 Hz](#)

Series:

- [Series L and P](#)

Primary Impedance Ohms_text:

*500 ct

Frequency Response Range:

- [300 Hz to 75 KHz](#)

Frequency Response:

3

Maximum Voltage at 1 KHz (Volt):

17.32

Maximum Voltage at 400 Hz (Volt):

14.14

Maximum Voltage at 300 Hz (Volt):

12.25

Custom Link:

13249