

## **F-28370**

Submitted by billnbdadmin on Wed, 07/24/2013 - 11:39

### **Product type:**

- [Audio Transformers](#)

### **Price:**

72.870

### **Secondary Impedance Ohms Split Windings SER:**

600 ct

### **Primary Impedance Ohms:**

4000.000

### **Secondary Impedance Ohms Split Windings PAR:**

150.000

### **Power Watts 1 KHz and higher:**

0.125

### **Power Watts 400 Hz and higher:**

0.020

**Primary Unbalanced DC Current ma:**

0.570

**Primary DC Resistance Ohms:**

400.000

**Secondary DC Resistance Ohms SER CONN:**

73.000

**Secondary DC Resistance Ohms PAR CONN:**

18.250

**Turns Ratio Prim/Sec SEC SER CONN:**

2.58:1

**Turns Ratio Prim/Sec SEC PAR CONN:**

5.16:1

**Product Sub-type:**

- [Thru Hole](#)

**Frequency:**

- [1 KHz](#)
- [400 Hz](#)

## Series:

- [Series F and G](#)

## Primary Impedance Ohms\_text:

4000 ct

## Frequency Response Range:

- [400 Hz to 250 KHz](#)

## Frequency Response:

3

## Maximum Voltage at 1 KHz (Volt):

22.36

## Maximum Voltage at 400 Hz (Volt):

8.94

## Custom Link:

13246